

# SP101 (Text To Speech SP101)

---

## Key Specifications/Special Features:

1. Desk Top Text to Speech Pager
2. Louder Speaker (98 dBA @ 30 cm)
3. Priority Message or Priority ID trigger relay and louder Emergency alarm ( bypass volume control )
4. Adjustable Speech Volume
5. Optional: Relay output
6. Support Language: English



SP101

---

## Sp101 Rich Sophistication:

---

- \* Large Memory Size; Total Capacity 42x24 Letters
- \* General Message: 24 sets
- \* 12hr or 24 hr format real time clock (selectable)
- \* Unread Message Reminder (LED flash)
- \* Convenient Functions; Auto Play, Hour memo, Prompt message, Set the length for Alert, Select Alert
- \* Message Time Stamp
- \* Priority Message or Priority ID trigger relay and Louder Emergency Alarm
- \* Up to 6 Capcodes for POCsAG

---

## Specifications:

---

Model	SP101
Frequency	138~174MHz, 408~473MHz, 929~932MHz (Pocsag), 929-932 (Flex)
Supply Voltage	DC12V
Frequency Stability	-10° to 50°C (+25°C ref.) 7 ppm for UHF, 10 ppm for VHF
Frequency Deviation	±4.5 KHz
Code Format	6 capcodes
Transmission speed	512 bps / 1200 bps / 2400 bps
Alert Tone Loudness	98 dBA @ 30 cm
Dimension	170(L) x 123.50(W) x 55(H)
Weight	402g

---

## Advantage:

---

This model is very helpful for the user to listen to the message directly without reading it. It can be located in the car for the driver to listen to the message while driving, or in the office to have all the staffs listen with its loud speaker when there is a message received.